



## Wireless two-way switch kit

For indoor lighting



Comfort

Guarantee **2** years

HelpLine  0 892 701 369\*

Ref. 500129

Gencod 3660215001291

### Technical characteristics

- ▶ 1 remote-controlled 230Vac-50Hz wired switch with built-in radio receiver
- ▶ Power : incandescent bulb : 300W maximum, halogen : 100W max, LED/compact fluorescent bulb/fluorescent tube : 5 to 500W, low voltage : 1A maximum
- ▶ Open air range : 150m
- ▶ Radio frequency : 868.3MHz
- ▶ 1 wireless 2-position wall remote control
- ▶ Operates with 1 27A 12V battery (included)
- ▶ Radio frequency : 868.3MHz
- ▶ The remote-controlled wired switch and the wall remote control are for indoor use only
- ▶ This product is connected in series with the lighting to be operated. It does not need to be connected to the phase

### Features

- ▶ This bundle allows you to create a two-way switch in a room that does not have one installed, without the need for any wires between the two switches. Simply replace the original switch with the one supplied and place the second surface-mounted switch wherever you wish. You can then switch on your lighting (max 300W) either locally from either of the switches or remotely via the optional remote control or using your smartphone and tablet. You may also incorporate it into your **Thombox** scenes, e.g. to automatically trigger lights to come on when a motion detector is triggered.

Connected  
**Home**